

PRV

PATENT- OCH REGISTRERINGSVERKET
Patentavdelningen

10/521 080 #2
DT15 Rec'd PCT/PTO 12 JAN 2005

Intyg Certificate

Härmed intygas att bifogade kopior överensstämmer med de handlingar som ursprungligen ingivits till Patent- och registreringsverket i nedannämnda ansökan.

This is to certify that the annexed is a true copy of the documents as originally filed with the Patent- and Registration Office in connection with the following patent application.



(71) Sökande St Jude Medical AB, Järfälla SE
Applicant (s)

(21) Patentansökningsnummer 0301201-0
Patent application number

(86) Ingivningsdatum 2003-04-24
Date of filing

Stockholm, 2003-11-18

För Patent- och registreringsverket
For the Patent- and Registration Office

Hjördis Segerlund

Hjördis Segerlund

Avgift
Fee 170:-

APPARATUS FOR ANALYSING CARDIAC EVENTS

Technical field

The present invention relates to an apparatus for analysing cardiac events
5 detected in electrograms, EGMs, and to a heart stimulator provided with such an apparatus.

In the following the expression cardiac event denotes the depolarization phase in the cardiac cycle which for atrial signals is commonly known as P wave and for ventricular signals as R wave or QRS complex.

10

Background

In the field of devices for cardiac rhythm management (CRM), accurate rhythm classification is an increasingly important aspect. Pacemakers are primarily used to assist in bradycardia or when the electrical propagation path is blocked,
15 whereas the primary use of implantable cardioverter defibrillators (ICD) is to terminate ventricular arrhythmia, a life-threatening condition if not acutely treated. In both types of devices, accurate event classification of the electrogram signal is needed for identifying, e.g., atrial and ventricular fibrillation in order to give appropriate therapy for the detected arrhythmia. For pacemakers, this may imply
20 changing the pacing mode in order to stabilize the ventricular rhythm during an episode of atrial fibrillation. An ICD responds to ventricular fibrillation by giving a defibrillatory shock which hopefully terminates the fibrillation.

Ever increasing demands are put on both kinds of devices to better handle their primary task as well as to manage other tasks than those originally intended for. One such task may, for an implantable medical device, be to identify atrial
25 flutter in order to terminate it by atrial pacing or to defibrillate atrial fibrillation. Although it is not a life-threatening arrhythmia, atrial fibrillation is an inconvenience to the patient and increases the risk for other diseases such as stroke. Atrial pacing may also be one way of terminating supraventricular tachycardias. An ICD
30 specific task is to identify atrial fibrillation in order to not mistake it for ventricular fibrillation and the risk of giving an unnecessary, and possibly harmful, defibrillation shock. Another, more general, utilization is to efficiently store rhythm data for later analysis and evaluation, already done in modern ICD's. By collecting

data, better knowledge of the evolution of cardiac diseases and the functionality of the device can be obtained.

Clustering represents an important task within the classification problem where each individual event is assigned to a cluster of events with similar features.

5 Labelling of the clusters, i.e., associating the cluster with a specific cardiac rhythm, completes the classification such that the device can provide proper therapy when needed. However, certain constraints distinguish clustering in CRM devices from clustering in general. In order to give immediate therapy, it requires clustering to be done in real-time, thus excluding many iterative clustering algorithms such as k-

10 means clustering and competitive learning. Various methods have recently been presented concerning clustering of signals from the surface electrocardiogram (ECG), based on, e.g., self-organizing maps or fuzzy hybrid neural networks, see M. Lagerholm, C. Peterson, G. Braccini, L. Edenbrabdt, and L. Sörnmo, "Clustering ECG complexes using Hermite functions and self-organizing maps", IEEE Trans.

15 Biomed. Eng., vol. 47, pp. 838 –848, July 2000, and S. Osowski and T. Linh, "ECG beat recognition using fuzzy hybrid neural network", IEEE Trans. Biomed. Eng., vol. 48, pp. 1265 –1271, November 2001. However, most clustering algorithms used for ECG analysis are computationally rather complex and therefore unsuitable for implantable CRM devices. Furthermore, not much a priori morphologic information is associated with the various rhythms in the electrogram (EGM); this is in

20 contrast to the more well-defined ECG.

Previously presented work in the area of intracardiac event classification mainly focus on discrimination of a specific condition in order to discern, e.g., atrial fibrillation from other atrial tachyarrhythmias, see A. Schoenwald, A. Sahakian, and

25 S. Swiryn, "Discrimination of atrial fibrillation from regular atrial rhythms by spatial precision of local activation direction", IEEE Trans. Biomed. Eng., vol. 44, pp. 958 – 963, October 1997. Other applications involve discrimination of ventricular from supraventricular tachycardia, see L. Koyrakh, J. Gillberg, and N. Wood, "Wavelet based algorithms for EGM morphology discrimination for implantable ICDs", in

30 Proc. Of Comp. In Card. (Piscataway, NJ, USA), pp. 343 – 346, IEEE, IEEE Press, 1999, and G.Grönefeld, B. Schulte, S. Hohnloser, H. - J. Trappe, T. Korte, C. Stellbrink, W. Jung, M. Meesmann, D. Böcker, D. Grosse – Meininghaus, J. Vogt, and J. Neuzner, "Morphology discrimination: A beat-to-beat algorithm for the discrimination of ventricular from supraventricular tachycardia by implantable

cardioverter defibrillators", J. Pacing Clin. Electrophysiol., vol. 24, pp. 1519 – 1524, October 2001. More general classification algorithms, which in turn involve training on individual patients, have been based on analogue neural networks or wavelet analysis for morphologic discrimination of arrhythmias.

- 5 Future pacemakers and ICD's will include more advanced means for arrhythmia detection and therapy, and the purpose of the present invention is to propose a technique for separation of cardiac rhythms in a reliable way on the basis of electrogram event clustering

10 ***Disclosure of the invention***

The above purpose is obtained by an apparatus according to claim 1.

- Certain arrhythmias are diagnosed immediately to give proper therapy, while, for others, it may be sufficient to record the rhythm for data collection purposes. Thus, the classification problem, viz. to label the rhythms based on
15 clusters using clinical terms, may not always be necessary to implement.

- According to advantageous embodiments of the apparatus according to the invention both morphologic and temporal data are considered for clustering. Morphologic features are efficiently extracted by use of the dyadic wavelet transform after which the events are grouped by a leader-follower clustering
20 embodiment. The event detection problem, based on the same transform, is previously treated in Swedish patent application no. 0103562-5.

- According to another advantageous embodiment of the apparatus according to the invention an integrating means is provided to integrate said distance over a predetermined period of time. By integrating the distance over a
25 period of time it is possible to distinguish irregular rhythms, like atrial fibrillation, from regular rhythms. The integral total distance in case of atrial fibrillation will be high whereas regular rhythms will result in a lower total distance.

- The invention also relates to a heart stimulator provided with the above mentioned apparatus for controlling the therapeutic stimulation depending on
30 arrhythmia detection.

Brief description of the drawings

To explain the invention in greater detail embodiments of the invention, chosen as examples, will now be described with reference to the enclosed

drawings, on which figure 1 shows impulse responses of a filter bank used for cardiac event detection, figure 2 is a flow chart of clustering algorithm perform with the apparatus according to the invention, figure 3 illustrates the computational complexity for different clustering algorithms, figure 4 presents in (a) clustering performance in terms of probability of a correct clustering of an event, P_{CC} and probability of a dominant event in a cluster P_{DE} and in (b) the spread in the number of clusters, figure 5 illustrates in (a) clustering performance in terms of P_{DE} and P_{CC} as a function of a distance threshold η and in (b) the numbers of clusters as a function of η , figure 6 exemplifies the clustering performance for one set of parameters, figure 7 exemplifies clustering result on a concatenated EGM for three cases, figure 8 is a flow chart illustrating the function in broad outline of an embodiment of the apparatus according to the invention, and figure 9 is a block diagram of an exemplifying embodiment of a heart stimulator provided with an apparatus according to the invention.

15

Description of preferred embodiments

P wave detection and feature extraction

A signal model assuming that the event waveform is composed of a linear combination of representative signals is considered. The feature extraction problem is then to estimate the individual components of the representative signals since each morphology will have its own linear combination. By using the dyadic wavelet transform, different widths of the two fundamental monophasic and biphasic waveforms are included in the model at a low cost.

Feature extraction

It is assumed that the QRS waveform is composed of a linear combination of representative signals,

$$H = [h_1, \dots, h_P] \quad (2)$$

where each function, h_j , $j = 1, \dots, P$, is of size $M \times 1$. The only restriction on H is that it must have full rank. Different morphologies, $s(n)$, are modelled by the $P \times 1$ coefficient vector $\theta(n)$, with the linear model

$$s(n) = H\theta(n) \quad (3)$$

where n is a temporal variable describing when the event occurs. The observed signal, $x(n)$, is assumed to be modelled by,

$$x(n) = H\theta(n) + w(n) \quad (4)$$

where the $M \times 1$ noise vector $w(n)$ is assumed to be zero-mean, white, and Gaussian with variance σ_w^2 . Consequently, $x(n)$ is defined as

$$x(n) = \begin{bmatrix} x(n) \\ \vdots \\ x(n+M-1) \end{bmatrix} \quad (5)$$

- 5 implying an event duration of M samples, beginning at n . The probability density function $x(n)$ for a specific realization of $\theta(n)$, $p(x(n); \theta(n))$, is thus given by

$$p(x(n); \theta(n)) = \frac{1}{(2\pi\sigma_w^2)^{\frac{M}{2}}} \exp \left[-\frac{1}{2\sigma_w^2} (x(n) - H\theta(n))^T (x(n) - H\theta(n)) \right] \quad (6)$$

- In this model, a complete description of a QRS complex is provided by the deterministic unknown parameter vector $\theta(n)$. The absence of a QRS complex corresponds to the case when $\theta(n)$ is equal to 0, where 0 is the $P \times 1$ zero vector. In general, no *a priori knowledge* is available on $\theta(n)$, and therefore an estimate is required before detection can take place. Furthermore, only one event is assumed to take place within the observation interval $0 \leq n \leq N$.

15

Filterbank representation

The descriptive functions in H have been selected such that the following three aspects have been taken into particular account:

1. the main morphologies of the QRS complex are mono- and/or biphasic
- 20 2. the broad range of QRS complex durations, and
3. a low complexity implementation.

- The wavelet transform is particularly suitable since it is a local transform, i.e., it provides information about the local behaviour of a signal. One wavelet decomposition method which may be efficiently implemented is the dyadic wavelet transform. By careful selection of the filters, a suitable filter bank including mono- and biphasic impulse responses can be obtained. A symmetric lowpass filter, $f(n)$, is used repeatedly in order to achieve proper frequency bands. This filter is combined with one of two filters, $g_b(n)$ or $g_m(n)$, which together define the

25

waveform morphology (the subindices b and m denote bi- and monophasic, respectively). For the biphasic case, the recursion is expressed as,

$$\begin{aligned}
 h_{1,b}(n) &= g_b(n) \\
 h_{2,b}(n) &= f(n) * g_b(2n) \\
 5 \quad h_{3,b}(n) &= f(n) * f(2n) * g_b(4n) \\
 &\vdots \\
 h_{q_{\max},b}(n) &= f(n) * \dots * \int (2^{q_{\max}-3}n) * g_b(2^{q_{\max}-1}n)
 \end{aligned} \tag{7}$$

in which the subindex q_{\max} represents the maximum (coarsest) scale.

10 It is now possible to present an expression for H which is composed of one biphasic and one monophasic part,

$$H = \begin{bmatrix} \tilde{H}_b & \tilde{H}_m \end{bmatrix} \tag{8}$$

15 where the biphasic H_b is defined as

$$H_b = \begin{bmatrix} h_{q_{\min},b} & \dots & h_{q_{\max},b} \end{bmatrix} = \begin{bmatrix} h_{q_{\min},b}(0) & \dots & h_{q_{\max},b}(0) \\ \vdots & \ddots & \vdots \\ h_{q_{\min},b}(M-1) & \dots & h_{q_{\max},b}(M-1) \end{bmatrix} \tag{9}$$

where the subindex q_{\min} represents the minimum scale and $q_{\min} < q_{\max}$. The
20 monophasic matrix H_m is computed in a corresponding way. The reversed order of the columns in \tilde{H} , denoted with \bar{H} in (8), is introduced in order to be consistent with the model assumed in (4).

In order to mimic the desired mono- and biphasic waveforms with a
low complexity filter bank structure, short filters with small integer coefficients were
25 used. In (7), the impulse response $f(n)$ was chosen as a third order binomial function,

$$F(z) = (1+z^{-1})^{L=2} = 1 + 3z^{-1} + 3z^{-2} + z^{-3} \tag{10}$$

where $F(z)$ is the Z-transform of $f(n)$. For the biphasic filter bank, the
30 filter $g_b(n)$ was selected as the first order difference,

$$g_b(n) = [-1 \ 1] \quad (11)$$

The filter $g_m(n)$ was chosen such that a compromise between the requirement of a DC gain equal to zero and an approximately monophasic impulse response was achieved. A reduction of complexity results when $g_b(n)$ is reused,

$$5 \quad g_m(n) = g_b(n) * g_b(n) = [1 \ -2 \ 1] \quad (12)$$

For this particular choice of $g_m(n)$ and by using Mallat's algorithm, it is possible to calculate both the biphasic and the monophasic filter output from each scale by using $f(n)$ once and $g_b(n)$ twice. The filter bank impulse responses are shown in Fig. 1. The filter bank includes two orthogonal signal sets where the width of the signal varies within each set. In (a), $h_{j,b}(n)$ is shown for $j = 2, \dots, 4$ from top to bottom, and in (b), the corresponding $h_{j,m}(n)$ are shown.

ML parameter estimation

The unknown coefficient vector $\theta(n)$ can be estimated by using the maximum likelihood criterion according to,

$$15 \quad \hat{\theta}(n) = \arg \max_{\theta(n)} p(x(n); \theta(n)) \quad (13)$$

However, $\hat{\theta}(n)$ is only of interest for those n for which the probability of an event, or, equivalently, for which the likelihood ratio test function $T(x(n))$ is maximized,

$$\hat{n} = \arg \max_n T(x(n)) \quad (14)$$

20 For this case, $T(x(n))$ can be shown to be [14],

$$T(x(n)) = x(n)^T H (H^T H)^{-1} H^T x(n) \quad (15)$$

for the case when σ_w^2 is assumed to be constant.

The optimal estimate $\hat{\theta}$ for the detected event at \hat{n} is thus expressed as

$$\hat{\theta} = \arg \max_{\theta(\hat{n})} p(x(\hat{n}); \theta(\hat{n})) \quad (16)$$

25 The MLE of $\theta(\hat{n})$ is found by maximizing $p(x(\hat{n}); \theta(\hat{n}))$, or equivalently minimizing the MSE,

$$(x(\hat{n}) - H\theta(\hat{n}))^T (x(\hat{n}) - H\theta(\hat{n})) = x(\hat{n})^T x(\hat{n}) + \theta(\hat{n})^T H^T H \theta(\hat{n}) - 2\theta(\hat{n})^T H^T x(\hat{n}) \quad (17)$$

Derivation with respect to $x(\hat{n})$ yields the optimum $\hat{\theta}$,

$$\hat{\theta}(\hat{n}) = (H^T H)^{-1} H^T x(\hat{n}) = (H^T H)^{-1} H^T x(\hat{n}) \quad (18)$$

By using the above formulation, it is also possible to derive a generalized likelihood ratio detector based on (15).

Rate

- 5 The central parameter for classification of cardiac arrhythmias is the heart rate. Most arrhythmias are defined in terms of heart rate, although sometimes with rather fuzzy limits. Consequently, rate should be considered in order to improve performance. The RR interval, Δt , is defined as the duration between two consecutive events,

$$10 \quad \Delta \hat{t}_k = (\hat{n}_k - \hat{n}_{k-1})T_s \quad (19)$$

where \hat{n}_k and \hat{n}_{k-1} denote the occurrence times of the events, and T_s denotes the sampling period.

Leader-follower clustering

- 15 The choice of leader-follower clustering is based on a number of features which makes it suitable for the present invention, viz.

- on-line processing (non-iterative), and
- self-learning, i.e., no a priori knowledge of the of clusters is needed.

- 20 The starting point is the assumption that an event is present for which it should be decided whether it belongs to an already existing cluster or if a new cluster should be initiated. Since, no knowledge is a priori available on which rhythms or morphologies to be expected, the chosen algorithm must be self-learning. The leader-follower clustering algorithm is constituted by four quantities:

1. The event parameter vector, $\Phi(n_k)$, containing the features of the k:th event that occurs at time n_k .
- 25 2. The cluster center, μ_i , and the covariance matrix Σ_i that together define the i:th cluster. Since both μ_i and Σ_i are unknown, they are replaced by their estimates $\hat{\mu}_i$ and $\hat{\Sigma}_i$, respectively.
3. The metric, d_i^2 , determine the distance between $\Phi(n_k)$ and μ_i .
- 30 4. A rule for adaptation of the cluster parameters for the winning cluster.

Initialization of new clusters

During run-time, a finite number of clusters exists which represent the rhythms having appeared until present time. Thus, it is occasionally necessary to initialize a new cluster when the existing ones do not sufficiently well fit the present event. When the distance function d_i^2 exceeds a certain threshold, η , it is more likely that the event belongs to a new cluster than to any of the existing clusters. The selection of η is a tradeoff between cluster size and cluster resolution in the sense that choosing a small η will result in many clusters with few clustering errors. On the other hand, a large η results in few clusters but in more errors.

The minimum distance between $\Phi(n)$ and μ_i with respect to both i and n is

$$d_{\min}^2 = \min_{i,l} d_i^2(l) \quad i=1, \dots, l \quad l = \hat{n}_k - \frac{K}{2}, \dots, \hat{n}_k + \frac{K}{2} \quad (20)$$

over the search interval K . The corresponding minimum distance indices are found as

$$[i_{\min}, n_{\min}] = \arg \min_{i,l} d_i^2(l) \quad (21)$$

The decision rule based on the comparison of d_{\min}^2 and η is expressed as

$$d_{\min}^2 \begin{cases} > \eta : \text{Initialize new cluster} \\ < \eta : \text{Assign to winning cluster} \\ < \rho \eta : \text{Update winning cluster} \end{cases} \quad (22)$$

where $0 < \rho < 1$. When the upper relation in (22) holds, a new cluster is initialized by first increasing the number of clusters by one, $l = l + 1$, given that $l < l_{\max}$ where l_{\max} is the maximum number of clusters, and then initializing the new cluster as,

$$\hat{\mu}_1 = \Phi(\hat{n}_k) \quad (23)$$

On the other hand, if $l = l_{\max}$ the algorithm needs to discard one of the existing clusters. This can be done by elimination of, e.g., the oldest or the

"smallest" cluster. By the term "smallest" cluster is meant that cluster which most rarely is fitted with a detected cardiac event.

For the middle and lower conditions in (22), the existing minimum distance cluster i_{\min} is selected as the winning cluster. However, only the lower condition
 5 results in a cluster parameter update. The reason for including such a distinction is that only closely similar events should be used for cluster updates in order to reduce contamination.

Mahalanobis distance function

10 The distance between the feature vector $\theta(n)$ and each cluster $\hat{\mu}_i$ is defined as the Mahalanobis distance, which is a normalized Euclidean distance in the sense that it projects the parameter vector elements onto univariate dimensions by including the inverse covariance matrix Σ_i^{-1} . Thus, a feature with a larger variance in $\Phi(n)$ will be assigned a larger share of the hyperspace before normalization compared to that with a lower variance. A consequence of normalization is
 15 that the Mahalanobis distance works well on correlated data since Σ_i^{-1} then acts as a decorrelator.

When searching for the minimum distance, a grid search over n is performed. This grid search is necessary since it not only minimizes the distance but
 20 also results in a more accurate fiducial point estimate than what would be the case when only considering $T(x(\hat{n}_k))$. The minimum distance is thus found by a grid search with respect to all existing clusters, $i = 1, \dots, I$, and all feature vectors within the duration of an event I as defined in (20),

$$d_i^2(l) = (\Phi(l) - \hat{\mu}_i)^T \hat{\Sigma}_i^{-1} (\Phi(l) - \hat{\mu}_i) \quad (24)$$

25

Reference feature adaptation

In order to track changes in the features of the different rhythms, adaptation of both $\hat{\mu}_{i_{\min}}(k)$ and $\hat{\Sigma}_{i_{\min}}^{-1}(k)$ are desirable; here the event index k has been included for clarity. For $\hat{\mu}_{i_{\min}}(k)$, an exponentially updated average is
 30 used:

$$\hat{\mu}_{i_{\min}}(k) = \hat{\mu}_{i_{\min}}(k-1) + \gamma \epsilon(k) \quad (25)$$

where

$$\varepsilon(k) = \Phi(n_{\min}) - \hat{\mu}_{i_{\min}}(k-1) \quad (26)$$

5 The exponential update factor γ is confined to the interval $0 < \gamma < 1$.

The inverse covariance matrix, $\hat{\Sigma}_{i_{\min}}^{-1}(k)$, is estimated by exponential averaging of the new cluster difference matrix $\varepsilon(k) \varepsilon^T(k)$ using the update factor $(1 - \alpha)$,

$$\hat{\Sigma}_{i_{\min}}^{-1}(k) = \left((\alpha) \hat{\Sigma}_{i_{\min}}(k-1) + (1-\alpha) \varepsilon(k) \varepsilon^T(k) \right)^{-1} \quad (27)$$

10

Using the matrix inversion lemma

$$A = B^{-1} + CD^{-1}C^T \quad (28)$$

$$A^{-1} = B - BC(D + C^TBC)^{-1}C^TB \quad (29)$$

15 and pairing the terms in (27) with the ones in (28),

$$A = \hat{\Sigma}_{i_{\min}}(k) \quad (30)$$

$$B^{-1} = \alpha \hat{\Sigma}_{i_{\min}}(k-1) \quad (31)$$

$$C = \varepsilon(k) \quad (32)$$

$$20 \quad D^{-1} = (1 - \alpha) \quad (33)$$

The inverse $\hat{\Sigma}_{i_{\min}}^{-1}(k-1)$ in (27) may be computed without any matrix inversions as,

$$\hat{\Sigma}_{i_{\min}}^{-1}(k) = \alpha^{-1} \hat{\Sigma}_{i_{\min}}^{-1}(k-1) - \frac{\alpha^{-1} \hat{\Sigma}_{i_{\min}}^{-1}(k-1) \varepsilon(k) \varepsilon^T(k) \alpha^{-1} \hat{\Sigma}_{i_{\min}}^{-1}(k-1)}{(1-\alpha)^{-1} + \varepsilon^T(k) \alpha^{-1} \hat{\Sigma}_{i_{\min}}^{-1}(k-1) \varepsilon(k)} \quad (34)$$

25 By utilizing the matrix inversion lemma, the computational complexity of the operation is reduced from $O(P^3)$ to $O(P^2)$.

Algorithm Initialization

In leader-follower clustering, clusters are initialized as they become needed. This feature is convenient since it does not automatically introduce any unused clusters. However, it also puts demands on the algorithm to be able to
 5 create new clusters when necessary, and also to terminate clusters either not used for long or with only a few events. Initially, the total number of clusters, I , is equal to one. The algorithm is initialized by assigning the parameter vector $\Phi(\hat{n}_1)$, which maximizes the test statistic in (14) of the first event, to the first cluster, cf. (23),

10

$$\hat{\mu}_1 = \Phi(\hat{n}_1) \quad (35)$$

For the general case, $\Phi(\hat{n}_k)$ is composed of a subset of the representative functions together with the preceding RR-interval,

15

$$\Phi(\hat{n}_k) = \begin{bmatrix} \hat{\theta}_s(\hat{n}_k) \\ \|\hat{\theta}_s(\hat{n}_k)\| \\ \Delta t_k \end{bmatrix} \quad (36)$$

Where $\hat{\theta}_s(\hat{n}_k)$ is a subset of the most discriminating elements in $\hat{\theta}_s(\hat{n}_k)$.

Note that an event is defined by its depolarization wave. Consequently, Δt is not included in the arrival time estimation σ , but instead computed afterwards.

20 The time continuous notation of Δt_k is preferred since it results in a suitable magnitude similar to the normalized morphological information in θ_s .

The inverse correlation matrix estimate is initialized in the same way for all clusters; a simple solution is to set it equal to a scaling of the identity matrix I ,

$$\hat{\Sigma}_i^{-1} = \delta I \quad (37)$$

25

where δ is a design parameter. The complete clustering algorithm for organized events is presented in the flow chart in Fig. 2.

Reduced-complexity clustering

In order to develop a more efficient algorithm in terms of performance
 30 versus power consumption and to evaluate the power consumption itself, a simple

measure of the computational complexity can be used, namely, the total number of multiplications. This quantity represents a much more complex operation than do additions. In this algorithm, where most operations are of the nature "multiply-accumulate", the number of additions is of the same order as the number of

5 multiplications and may thus be neglected without significant loss of accuracy.

In order to reduce the computational complexity, focus is put on reducing the number of multiplications. The dominant contributions of multiplication operations are found in (24) and (34) which require $P(P + 1)$ and $P/2 (3P + 5)$ multiplications, respectively, considering certain symmetry properties of $\hat{\Sigma}_i^{-1}$.

10 Furthermore, one division is required in (34). However, according to (20), (24) is performed IK times per event while (34) is performed only once per event.

Based on the above performance figures, a few approximations can be identified:

- o to use only the peak(s) in $T(x(\hat{n}))$ instead of a complete grid search,
- 15 o to use a simplified $\hat{\Sigma}_i^{-1}$, and
- o to use a likelihood based search sequence over the clusters, i.e., to start with the most likely cluster and to stop the search if a sufficiently small distance is found.

Simplifying the grid search from spanning both samples and clusters
20 in (20) to span over only clusters,

$$d_{\min}^2 = \min_i d_i^2(\hat{n}) \quad (38)$$

the number of multiplications may be reduced by a factor K to $IP(P + 1)$. Due to sensitivity in $T(x(\hat{n}))$, the feature vectors resulting in the peaks for two different events may differ significantly, this simplification is likely to result in more
25 clusters. A useful compromise may instead be to use the coefficients from, e.g., the 3 largest peaks in $T(x(\hat{n}))$ resulting in $3IP(P + 1)$ multiplications per event.

Since a cardiac event lasts for longer time than one sample those samples which give the filter coefficients which are most similar to the cluster reference are determined. A grid search over 40 msec is preferably made. In this
30 way coefficients of greatest importance locally are determined. For this decision

$T(x(n))$ is considered and samples generating a peak are chosen, i.e. $T(x(n-1)) < T(x(n)) > T(x(n+1))$, since they indicate the probability for the presence of an event.

Another simplification, based on the approximation of orthogonality between the different wavelet scales as well as the RR interval, is to simplify $\hat{\Sigma}_i^{-1}$ by only including its diagonal elements in the adaptation,

$$\hat{\Sigma}_{i_{\min}}^{-1} \approx \alpha^{-1} \hat{\Sigma}_{i_{\min}}^{-1} + (1 - \alpha) \text{diag}(\epsilon(k) \epsilon^T(k)) \quad (39)$$

where $\text{diag}(A)$ returns the diagonal elements of the square matrix A . By using this approximation, the number of multiplications used for the estimation of $\hat{\Sigma}_i^{-1}$ is reduced to $3P$. Additionally, the distance computation in (20) is simplified and may be reduced to $2IKP$ multiplications per event.

A reasonable assumption is often that successive events originate from the same rhythms. Considering this knowledge, it would be sufficient to compute the distances for the previously selected cluster. In doing so, the number of multiplications in (38) are reduced even further.

Table 1 presents the different detector versions as defined by their distinguishing features and shows computational complexity for the different versions of the clustering algorithm.

Version	Features		Complexity C
	$\hat{\Sigma}_{i_{\min}}^{-1}$	Search alg.	
A	Full	Interval	$IKP(P + 1) + \frac{P}{2} (3P + 5)$
B	Diagonal	Interval	$2IKP + 3P$
C	Full	3 peak	$3IP(P + 1) + \frac{P}{2} (3P + 5)$
D	Diagonal	3 peak	$6IP + 3P$

The total computational complexity, C , as reflected by the number of multiplications for the different algorithm versions, is presented in Fig. 3 as a function of I . In figure 3 the solid line shows an algorithm version A, dashed line a

version B, dotted line a version C, and a version D by dash-dotted line), for a feature vector with (a), $P = 4$, and (b), $P = 7$ elements.

Results

5 The results are obtained by studying the performance of the following quantities:

- o algorithm versions, as presented in Table 1, and
- o noise tolerance, for noise-free signals and for signals with background noise of $50\mu\text{V RMS}$.

10 The following parameter settings have been used (unless otherwise stated),

$$\alpha = 1.05 \quad \gamma = 0.025 \quad \delta = 50 \quad K = 40 \quad (49)$$

15 It is noted that α^{-1} is chosen to offer faster adaption than γ . The reason for that is that the initial estimate $\hat{\Sigma}_i^{-1}$ is likely to be less accurate than the initial estimate $\hat{\mu}_i$. Also, δ is chosen to have the same order of magnitude as the steady state eigenvalues $\hat{\Sigma}_i^{-1}$.

It should be noted that the different algorithm versions are not fully
20 comparable in terms of performance for a specific due to the differences in distance computation. In versions B and D, where a diagonal $\hat{\Sigma}_{i_{\min}}^{-1}$ is used, the lack of non-diagonal information results in a nonorthogonal distance which is larger than the orthogonal one. Since versions C and D make use of a limited search, the minimum distance found may differ from the global minimum
25 distance for the event. Both these algorithmic differences imply an increase in clustering quality for a certain value of η , however, at the expense of more introduced clusters.

Evaluation measures

30 The two main quantities evaluated are clustering performance and computational complexity, see Fig. 3; these two quantities are in general conflicting. In the evaluation, a cluster is assigned to that cardiac rhythm which

contains the most events in the cluster. This rhythm is denoted as the dominant rhythm within the cluster. With respect to the dominant rhythm, the cluster is defined as a correct cluster, whereas it is erroneous to all other rhythms. If a rhythm is found to be dominant in more than one cluster, such clusters are first merged in the performance evaluation. The number of events in the correct cluster which belongs to the i :th dominant rhythm is equal to $N_D(i)$, while the number of events belonging to any other false rhythm in the cluster is equal to $N_F(i)$. The number of events of the dominant rhythm which are not classified in a correct cluster, i.e., missing, is equal to $N_M(i)$.

- 10 The performance of the algorithm is evaluated in terms of probability of a correct clustering of an event, $P_{CC}(i)$, and probability of a dominant event in a cluster, $P_{DE}(i)$. The first parameter is expressed as the share of correctly clustered events within a rhythm and is, using the above parameters, defined by

$$P_{CC}(i) = \frac{N_D(i)}{N_D(i) + N_M(i)} \quad (41)$$

- 15 The second parameter may be expressed as the share of dominant rhythm events within a cluster, and is defined as

$$P_{DE}(i) = \frac{N_D(i)}{N_D(i) + N_F(i)} \quad (42)$$

- For the case when a rhythm completely lacks a correct cluster, $P_{DE}(i)$ is undefined; the rhythm is then excluded from subsequent statistical computations. Averaging $P_{CC}(i)$ and $P_{DE}(i)$ over all clusters results in the global performance measures P_{CC} and P_{DE} , respectively.

- 25 It should be pointed out that $P_{CC}(i)$ and $P_{DE}(i)$ reach their maximal value of 1 when n is sufficiently small such that the number of clusters equals the total number of beats evaluated. This is, of course, a highly undesirable solution although performance, as expressed in (41) and (42), will be excellent. For this reason, the total number of clusters, I , is a crucial parameter to be considered. Here, the average \bar{I} is used together with the minimum and maximum number of clusters for a case, I_{min} , and I_{max} , respectively.

- 30 The power consumption of the algorithm is an important parameter which determines the pacemaker life span. In this study, power consumption is approximated by the computational complexity defined above as the total number of multiplications. As shown, the computational complexity depends mainly on

three parameters: the feature vector length, P , the search interval, K and the cluster size, I .

Noise-free signal clustering performance

Figure 4 presents clustering performance in terms of P_{DE} and P_{CC} , see Fig. 4 (a), and I_{min} , \bar{I} and I_{max} , see Fig. 4 (b). Thus in figure 4(a) clustering performance is shown as depending on \bar{I} for P_{CC} (dark bars) and P_{DE} (bright bars) for noise-free signals. In figure 4(b), the spread between the different cases is shown as, from left to right, I_{min} , \bar{I} and I_{max} . The presented algorithm versions are found in Table 1 and three values of have been chosen for comparison; 3, 4 and 5. Versions A and B perform similarly for all three cases, and achieve $P_{DE} = 1$ and $P_{CC} = 1$ for $\bar{I} = 4$ and $\bar{I} = 5$, respectively, by creating an acceptable number of clusters. However, it can be seen from Fig. 4 (b) that a large difference in the number of initialized clusters between different cases is present. For version B, a slight increase in both \bar{I} and I_{max} is observed for $\bar{I} = 4$. However, this increase is more due to an unfortunate step-like behaviour in the results for the given \bar{I} than for any significant decrease in performance. The values of η used in Fig. 4 for the different versions are shown in Table 2.

Table 2: Values of η used in Fig. 4.

\bar{I}	Algorithm version			
	A	B	C	D
5	3.6	4.2	5.4	5.8
4	4.6	4.8	7.0	7.2
3	9.6	9.6	12.0	10.8

20

Versions C and D perform slightly worse than do versions A and B. Contrary to the latter ones, neither version achieves $P_{DE} = 1$ or $P_{CC} = 1$ for the presented \bar{I} , see figure 4(a).

Figure 5 (a) presents the clustering performance for version A in detail and its dependence on η . The most noteworthy result is that both $P_{DE} = 1$ and $P_{CC} = 1$ for $\eta < 7$. It is also clear that clustering performance deteriorates rapidly for $\eta > 10$. The increase in P_{CC} for very high values of η is due to that not all rhythms are allocated to a dominant cluster and are therefore disregarded in the performance computation.

25

In Fig. 5 (b), I_{min} , \bar{I} and I_{max} are presented as a function of the clustering threshold. Thus figure 5(a) shows clustering performance in terms of P_{DE} (solid line) and P_{CC} (dashed line) as a function of η for noise-free signals, and figure 5(b) the corresponding I_{min} , \bar{I} and I_{max} . For $\eta < 3$, the number of initiated
 5 clusters increases rapidly with decreasing η . Within the interval $3 < \eta < 7$, all rhythms initiate at least one cluster, while for $\eta > 7$, this is not true for all cases. Removing the "worst case", the above is true for the other cases for $\eta < 10$.

The clustering performance is exemplified for one set of parameters in Fig.6 using $\eta = 7$. Correct clustering with minimal number of clusters is achieved
 10 for two cases while an extra cluster is initialized for two cases. The reason for the extra cluster is that, for case 2, the temporal search interval is chosen too small for the third morphology from the left resulting in an extra cluster. For case 5 an actual difference in morphologies both on the up and down slopes of the dominant peak is discernible between the first and fourth clusters from the left.

15 Clustering for a concatenated electrogram is presented for case 3 in Fig. 7, where three distinct rhythm classes can be discerned, viz. normal sinus rhythm followed by supraventricular tachycardia and atrial flutter. The EGM is shown together with the clusters, represented by o, x and +, respectively, assigned for each event.. The different rhythms result in three clusters.

20 Figure 8 is a flow chart illustrating the function in broad outline of an embodiment of the apparatus according to the invention. At block 2 cardiac event features are extracted in the form of wavelet coefficients, and the event is detected, at 4, 6. At block 8 is checked whether the detected event is member of a labelled cluster. If so, the event is added to a class, at 10, and actions associated
 25 with that class are performed, at 12.

If the event is not member of a labelled class it is checked if it is a member of an existing cluster, at 14. If so, the event the event is added to a class, at 16, and it is checked if it is possible to label the cluster, 18, and if so the cluster is labeled, at 20.

30 If the event is not a member of an existing cluster, block 14, a new cluster is created as described above fitted to the detected cardiac event, at 22.

Thus according to the invention clustering events in the EGM is performed for use in implantable CRM devices, like heart stimulators. The invention is based on feature extraction in the wavelet domain whereupon the

features are clustered based on the Mahalanobis distance criterion. According to advantageous embodiments of the apparatus according to the invention simplifications of the technique is proposed in order to reduce computational complexity to obtain a more implementationally feasible solution.

5 If the apparatus according to the invention is to be used for longer periods of data analysis, large clusters, although old, may be desirable to be kept in some way, while the oldest cluster may be selected to be removed if the application is based on shorter time frames. Also, due to the short data lengths, testing of such algorithms would be of limited value.

10 By combining detector/clusterer with labelling rules of a classifier a complete detector/classifier is obtained with the possibility to more accurate therapy.

The labelling need not be done in real time and probably more than one event will be needed to label a cluster. Once the cluster has been labelled
15 using clinical terms, the actions associated with the particular class will be carried out immediately, i.e. in real time. Thus, the rules needed to label the cluster are not used in identifying the event itself.

The rules used to label the clusters are based on characteristics of the different possible events. Instead of the exact rules, the characteristics are
20 consequently described.

Figure 9 is a blockdiagram of an embodiment of an implantable heart stimulator provided with the apparatus according to the invention. Electrodes 30, 32 implanted in the heart 34 of a patient are connected by a lead 36 to an A/D converter 40, via a switch 38 serving as overvoltage protection for the A/D
25 converter 40. In the A/D converter 40 the signal is A/D converted and the digital signal is supplied to a wavelet detector 42.

The detector 42 decides whether a cardiac event is present or not as described earlier. Wavelet coefficients are calculated as well. Parameters of the detector 42 are programmable from the stimulator microprocessor 44. At the
30 detection the coefficients and the RR information are forwarded to the clusterer 46 in which it is determined to which cluster the detected cardiac event belongs, as described previously. The clusterer 46 is preferably of a leader-follower type and also the cluster parameters are programmable from the microprocessor 44.

By the microprocessor 44 suitable therapy is decided depending on assigned cluster for the detected event and possible a priori knowledge about arrhythmia associated with the cluster in question. Thus it is possible to distinguish e.g. ventricular tachycardia from a sinus tachycardia by comparing the parameters with a known normal sinus rhythm. Parameters of the sinus tachycardia are then supposed to be similar to those of a normal sinus rhythm, whereas parameters of ventricular tachycardia differ significantly.

As an alternative the decision rules can be trained from a number of rhythms and the resulting rules are then used on test data, see Weichao Xu et al., "New Bayesian Discriminator for Detection of Atrial Tachyarrhythmias", DOI:10.1161/01.CIR.0000012349.14270.54, pp.1472-1479, January 2002. It is then possible to decide that a certain position of the cluster indicates e.g. a sinus rhythm, etc. Also this technique can be based on analysis of the feature vector for a cluster, and it is possible to decide if the beat is broad or narrow, large or small, or if the rhythm is regular or irregular.

The stimulator in figure 9 also includes a pulse unit 48 with associated battery 50 for delivery of stimulation pulses to the patient's heart 34 depending on the clustering evaluation.

The implantable stimulator shown in figure 9 includes telemetry means 52 with antenna 54 for communication with external equipment, like a programmer.

CLAIMS

1. An apparatus for analysing cardiac events detected in electrograms, EGMs, **characterized in** that a feature extraction means is provided to derive
5 features of said cardiac events for discriminating different kinds of detected cardiac events, and in that a clusterer is provided to group cardiac events with similar features into a cluster, defined by predetermined cluster features.
2. The apparatus according to claim 1, **characterized in** that said feature
10 extraction means is adapted to determine a feature vector describing waveform characteristics of cardiac event EGM signals.
3. The apparatus according to claims 1 or 2, **characterized in** that said
15 feature extraction means is adapted to perform morphological analysis on cardiac event EGM signals for the discrimination of different kinds of detected cardiac events.
4. The apparatus according to any of the preceding claims, **characterized in**
20 that said feature extraction means is adapted to determine the cardiac rate as one of said features.
5. The apparatus according to claim 2, **characterized in** that said clusterer is
25 adapted to determine the distance between said feature vector and corresponding cluster feature vectors to assign the cardiac event in question to that cluster which results in a minimum distance.
6. The apparatus according to any of the preceding claims, each cluster
being defined by a cluster center μ_i and a covariance matrix Σ_i for the respective
cluster features, **characterized in** that said clusterer is adapted to determine a
30 distance function d_i^2 between event feature vector and said cluster center μ_i .
7. The apparatus according to claim 6, **characterized in** that said clusterer is
adapted to calculate said distance by using Mahalanobis distance criterion.

8. The apparatus according to claim 6 or 7, **characterized in** that said clusterer is adapted to determine the minimum of said distance by a grid search over the duration of the event.

5 9. The apparatus according to any of the preceding claims, **characterized in** that an integrating means is provided to integrate said distance over a predetermined period of time.

10 10. The apparatus according to any of the preceding claims, **characterized in** that said clusterer is adapted to update cluster features according to a predetermined rule on the basis of the difference between cluster features and event features.

15 11. The apparatus according to any of the preceding claims, **characterized in** that said clusterer is adapted to create a new cluster, if the difference between features of a detected cardiac event and features of existing clusters exceeds a predetermined limit, by setting features of a new cluster equal to the event features of the cardiac event in question.

20 12. The apparatus according to any of the preceding claims, **characterized in** that said clusterer is adapted to terminate clusters not, or only rarely, being provided with detected cardiac events within a predetermined time period.

25 13. The apparatus according to any of the preceding claims, **characterized in** that said clusterer is adapted to perform a likelihood based search sequence over the clusters to determine the minimum of said distance.

30 14. The apparatus according to any of the claims 8 - 12, **characterized in** that said clusterer is adapted to span said grid search only over the clusters.

15. The apparatus according to any of the claims 1 - 14, **characterized in** that said clusterer is adapted to calculate the distance of a considered cardiac event from the previously selected cluster.

16. The apparatus according to any of the preceding claims, **characterized in** that a classifier is provided to associate the clusters with different specific cardiac rhythms according to predetermined rules.
- 5 17. A heart stimulator, **characterized by** an apparatus according to any of the preceding claims for on-line arrhythmia detection and control means for controlling the therapeutic stimulation depending on said arrhythmia detection.
-

9
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211

ABSTRACT

An apparatus for analysing cardiac events detected in electrograms, EGMs, comprises a feature extraction means (42) provided to derive features of said cardiac events for discriminating different kinds of detected cardiac events. A clusterer (46) is provided to group cardiac events with similar features into a cluster, defined by predetermined cluster features. A heart stimulator is provided with such an apparatus for arrhythmia detection and control means (44) for controlling the therapy depending on the arrhythmia detection.

10

(Figure 9)

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100

1/8




Fig. 1




Fig. 2

3/8




Fig. 3




Fig. 4

4/8




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9